SHERLOCK

DISK UTILITY

RANTON
Microcomputer Software

SHERLOCK

version 2·2

copyright 1982

the FOURTH WORKS , INC

Congratulations on purchasing what we feel
to be the finest ATARI disk utility program
currently on the market. With SHERLOCK you
will be able to examine any byte in any sector,
change any byte in any sector, disassemble (from
disk, not core) any machine language file or
autoboot disk, make a sector map of a diskette,
format disks, search for up to 32 bytes in any
sector on a disk in either HEX or ASCII format,
and other useful utilities -- all at machine
language speed!
        SHERLOCK is a menu driven utility.   A
thorough reading of the documentation is
recommended to fully utilize all of SHERLOCK's
features. For novice disk drive users, a short
tutorial is included -- read this carefully for
clear understanding.

SYSTEM REQUIREMENTS

ATARI 800/400
ATARI 810 DISK DRIVE   OR
PERCOM RFD 40 TRACK DISK DRIVE
32K RAM (MINIMUM, 48K RECOMMENDED)
PRINTER (OPTIONAL)

        SHERLOCK is copy protected.   The program is
on both sides of the supplied diskette.   Should
your diskette fail to boot at any time within 90
days, return it to Rantom Software, and it will
be replaced at no charge. After 90 days, a
nominal charge of $7.50 will be charged.

BOOTING SHERLOCK:

        Remove all cartridges.
        Turn on your disk drive.   After the busy light
goes out, insert SHERLOCK and turn on your
computer.   RANTOM PRESENTS SHERLOCK will
be displayed, then SHERLOCK's menu.   Choose
the option of your choice, enter the number, then
press return.

TUTORIAL FOR NOVICE USERS

In using SHERLOCK, bytes in a sector are
numbered from $1 to $80 HEX (1 to 128
DECIMAL) and sectors are numbered from $1 to
$2D0 HEX (1 to 720 DECIMAL)

SHERLOCK is a floppy disk utility program.
A floppy disk is nothing more than a circular
piece of material with an oxide coating capable
of storing magnetic pulses. A formatted ATARI
diskette organizes these magnetic pulses in a
specific manner. There are 40 concentric rings
on an ATARI diskette. These rings are called
tracks, so the ATARI 810 disk drive is a 40 track
disk drive. Each track is divided into 18 areas,
called sectors. Each sector contains 128 pieces
of information called bytes. There are a total of
40 tracks, 720 sectors, and 92,160 bytes on a
formatted Atari diskette. Remember, tracks,
sectors, and bytes are nothing more than
magnetic pulses stored on a diskette. They
cannot be seen or felt. Do not touch the surface
of a diskette, because it is very susceptible to
damage by body oils, scratches, and dents on
their surface. Also, do not expose your diskette
to any type of a magnetic field, because this can
destroy any data that is stored on the diskette.
Do not put your diskettes within 6 inches of a
television set (or monitor), telephone, or any
other source of magnetic fields. SHERLOCK will
allow you to see the value of any of the 92,160
bytes stored on a diskette, and allow you to
manipulate those bytes in any manner that you
choose.

When a diskette is formatted, 720 blank
sectors are written on the diskette. Initially all
of these sectors are filled with zeros (0). This
indicates to the computer that the diskette is
void of information, yet ready to store
information. After the actual formatting
process, the DISK OPERATING SYSTEM (DOS)
reserves and writes to certain sectors on the
diskette in sectors 1 through 3. The information
stored here is called the DOS bootstrap. When
the ATARI computer is turned on, an internal
program stored in READ ONLY MEMORY (ROM)

is executed. This program checks to see if a
disk drive is connected to the system (and turned
on). If not, the computer turns control over to
whatever cartridge is in the left slot. If no
cartridge is in the left slot, the control is
turned over to the MEMO PAD mode. If a disk
drive is connected and turned on, then the
diskette in the drive will be read starting with
sector number 1. The first six bytes in sector
number 1 are very important. This sector is
called the "BOOT SECTOR". If you have not
already loaded SHERLOCK, do so now. After the
program is loaded and the busy light on the disk
drive is out, remove SHERLOCK and return it to
it's protective jacket. Now insert a diskette
into your disk drive on which you know has DOS
written on it. Now select option number 1 for
"DUMP SECTOR" and hit return. Answer the
prompt with a "1" and hit return. Displayed on
the screen is the contents of sector number 1 in
both the HEX and the ASCII formats. For now
ignore the ASCII side. Look at the first row of
numbers on the HEX side of the screen. We are
only interested in the first 6 pairs of numbers.
If you have a DOS 2.0S disk in your drive, these
numbers should be: --- 00 03 00 07 40 15 --- Byte
number 1 is not significant, and is usually 00 or
FF. Byte #2 is the number of sectors to be read
into memory -- the number of "BOOT SECTORS".
In our example there are three "BOOT
SECTORS". Byte numbers 3 and 4 tell the
computer where in memory to start storing the
incoming 3 sectors of information. In this
example the memory location is $0700 (HEX).
You may wonder how I got $0700 out of 00 07.
The reason for this is that the ATARI stores
memory location addresses with the low byte
first, then the high byte. If this is confusing,
just remember that when you are dealing with a
memory location address, such as 00 07, all you
have to do is transpose the two sets of numbers
to get 07 00 -- so, the correct address is $0700.
Bytes 5 and 6 are also an address. This tells
the computer what address to go to and start
program execution AFTER all of the "BOOT
SECTORS" have been loaded. Therefore, after
the three boot sectors of this example have been
loaded into memory starting at $0700, control

will be given to the program starting in memory
location $1540. This is a location in the 10K
OPERATING SYSTEM (OS). All DOS 2.0S disks
should have the same information in the first 3
sectors. After you've finished reading this
tutorial, insert an autoboot game diskette and
see how this differs from DOS. They only
numbers that are likely to be the same are the
pair of numbers in byte #1, and as we discussed
earlier, this byte, for our purposes, is
insignificant.

VTOC

   After the format process, DOS writes to
other sectors besides 1, 2, & 3. It writes to
sectors 360 to 368 (DECIMAL). This is where
the VOLUME TABLE OF CONTENTS (VTOC) and
the DISK DIRECTORY is stored. Use option
number 1 of SHERLOCK again and look at sector
$168 ($168 HEX = 360 decimal. All input to
SHERLOCK, except for menu selections, is in
HEX. For help in conversions, use option number
9 - "NUMBER CONVERSION"). On a DOS disk,
the first two bytes are 02 C3. This means that
there are a maximum of $2C3 (707 DECIMAL)
sectors on the disk available for your use. The
next two bytes can be anything from 0 to $2C3.
This tells the computer how many of the $2C3
sectors available to you are actually empty of
information. The other numbers seen in this
sector tell you which sectors on the disk contain
information and which sectors are empty. For a
detailed description of how this works, refer to
your DOS 2.0S manual and/or the Technical
Users Notes.

DISK DIRECTORY

Sectors $169 through $171 contain the DISK
DIRECTORY. These sectors contain the names
of the files on a DOS disk, their length and
status -- locked, deleted, opened, etc. Without
the DISK DIRECTORY you would not be able to
tell what programs of files you have stored on a
diskette. If you still have a DOS disk in your
drive, use option number 1 and look at sector
$169. The file or program starts in byte $06 and
the extension in byte $0E. If the program name
does not contain 11 characters (including the
extension) spaces fill out the name field. File
names start every 16 (DECIMAL) bytes --
allowing for 8 entries per sector. Since there
are 8 sectors reserved for the DISK
DIRECTORY, you are allowed up to 64
(DECIMAL) files per diskette. The first byte of
every entry is the status byte for that
particular file. If the file is unlocked the
number will be $42. If locked $62. If deleted
$80. Occassionally, a file may be opened for a
read operation and before the file is properly
closed the user will turn off the computer.
Should this happen, the status byte will be $43.
As far as the computer is concerned, this file
does not exist. The file has neither an "in use"
status byte, nor a "deleted" status byte, so it is
in limbo, and just taking up directory space. To
regain the directory space, change the status
byte (using SHERLOCK option number 2) to $80.
The second and third bytes in a directory entry
contain the size, in sectors, of the file. Again,
like an address, low byte first, then high byte
(just transpose the numbers like before). The
fourth and fifth bytes tell you (low/high) the
beginning sector number of that file.

SECTOR LINKS

When a file is written to a DOS disk three
bytes of each sector are reserved for DOS use.
These sectors tell DOS how many bytes of
information are in the current sector, and where
the next sector to be read is located. The bytes
reserved are bytes $7E,7F, and $80. When you
write a file to a diskette, DOS will try to write
that file in contiguous sectors. If there are not
enough contiguous sectors available, the DOS
will look for available empty sectors to write
the remainder of the file. Because you can't
count on one sector calling the next sequential
sector, you must have a way to tell DOS where to
find the next correct sector to load. Again, to
understand precisely how there last three bytes
are used, consult the DOS 2 manual and/or the
Technical Users Notes.

The preceding was meant to be a very fast
and dirty tutorial on the structure of ATARI
DOS diskettes. For more information, carefully
read the DOS 2 manual and the portion of the
Technical Users Notes dealing with disk booted
software.

INSTRUCTIONS FOR USING SHERLOCK

At any time there could be a chance of writing to the wrong disk, as in editing, copying, and formatting, the border will change to red as a warning. At almost any point in the program, you can press 'P' and get a screen dump to the printer.

1) DUMP SECTOR

Select option number 1. You will then be asked which sector (in HEX) you would like to have displayed to the screen. Enter the sector number and hit return. On the left is the HEX representation of the sector, and to the right the ASCII representation. To dump the screen contents to a printer press "P". Press either the left or right arrow keys to see previous or following sectors. Should you attempt to view non-existant sectors (less than $1 or greater than $2D0) SHERLOCK will return to the main menu. To return to the main menu press any key other than "P" or the left and right arrow keys.

2) EDIT SECTOR

Select option number 2. Enter the sector number you wish to edit and press return. You will be asked if you would like to zero the sector --- answer yes or no. Now you will be asked if you want to edit in the HEX or ASCII mode. Unless you choose the "A" option, the program will default to the HEX mode. In the HEX mode, 0 through 9 and A through F are legal keys. All others are trapped out. In the ASCII mode, all keys except arrow keys, are legal. In either mode, cursor movement is achieved by using the four arrow keys. Holding down the CTRL key is NOT required, nor will it move the cursor. Change the sector information in any manner you wish. When completed, press return. You will be asked if the changes are correct. If you answer no, the sector will be re-read from the disk and displayed. If you answer yes, you will be asked if you want to write the sector with

your changes back to the disk in the same
location. Answer yes and the sector will be
written and you will be returned to the main
menu. Answer no and you will be asked to what
sector you want to write the information. The
information will them be written to the location
you specified and you will then return to the
main menu. If you realize that you don't want to
write to the disk at all and just want to abort
the option, enter a zero (0) for the sector to be
written or press SYSTEM RESET.

3) DISK MAP
        Select option number 3. After return is
pressed, what ever diskette is currently in the
drive it will be read and a graphic
representation of it's contents will be displayed
on the screen. An asterisk (*) indicates that a
sector sector has valid information in it
(non-zero). A period (.) means the sector is
totally empty (all zeros). A hyphen (-) indicates
that the sector is unformatted. Each row of *'s,
.'s, and -'s represent 2 tracks. After the map is
completed a hex number index is displayed on the
left side of the screen to help you locate the
sectors you are interested in. Should you wish
to abort the map before completion, just hold any
of the yellow keys.
        NOTE: For users who do not have a DATA
SEPERATOR installed in their disk drive,
occassionally, the map will indicate that you
have unformatted sectors in the last two or
three tracks on a disk you know to be good. This
is not an error in SHERLOCK, but a problem with
your disk drive. There are two solutions to this
problem. 1 -- Go to your nearest ATARI Service
Center and have a DATA SEPERATOR installed
or 2 -- Recognize the problem and live with it.
If you are having problems reading sectors in
other tracks, and you know the disk being
mapped does not have unformatted sectors, go to
an ATARI Service Center and have your disk
drive speed checked and corrected.

4) DISK DISASSEMBLER

Select option number 4. You will be asked if
you want a print out of the disassembled code.
Answer yes or no. Input the sector number to
start disassembly. If you enter sector 1, then
you will be asked if you want to use the first six
boot bytes -- answer yes or no. If this point is
confusing, read the tutorial supplied. Now,
enter the address of the first byte in the sector
you choose to disassemble. Now enter the
address of where you want disassembly to begin.
This may seem rather confusing, however, there
is a purpose. Suppose you know the beginning
address of sector $1 is $0700 and you really
want to look at the code beginning at $0900.
Answer 1 for the sector to start disassembly.
Answer yes for the boot bytes. Answer $0700
for the first byte in the sector. Answer $0900
for the address you want to disassemble from.
SHERLOCK will figure out where $0900 would be
in relation to the beginning address of $0700. In
this example, $0900 is located in sector 5.
    If you have not chosen the print option, you
must press the START key for the disassembly
to continue. The disassembly to screen is
relatively fast. If you see a portion of code you
want to examine more closely, release the
START key, and the disassembly will pause. To
continue, press the START key again. To abort
and return to the menu press the SELECT key.
    If you did select the print option, then
holding the START key could be inconvenient,
especially if you wish to print several pages of
disassembly. With this option, disassembly will
start and continue until the option is aborted
with the SELECT key. In the print mode, the
disassembly will be displayed to the screen as
well as the printer. Should you choose not to
use the print option, and would rather use the
screen dump option instead, you must hit a key
(any key) before pressing 'START' to continue
the disassembly.

5) DISK SEARCH

Select option number 5. You can search for up to 32 bytes in either HEX or ASCII mode. You will be asked if you would like to search for HEX or ASCII. Unless you specify ASCII, you will default to HEX. If you are in the HEX mode, just enter the HEX code to be searched for. Make sure you type a space between each pair of numbers. For example, if you want to search the disk for the code LDA #$21, the HEX code would be A9 21. That is what you would enter -- A9 21. You will be asked which sector you want the search to begin with. When a match is found, the sector will be displayed to the screen -- in the same format as the Dump Sector option, with an arrow pointing to the first byte of the sequence you were searching for. You will be asked to enter a "Y", "N", "P", or "D". If you want to continue the search for the same sequence, enter "Y". If you do not want to continue the search enter "N". If you want to print the screen contents enter "P". If you wish to see the code in disassembled form enter "D". Answer "N" and you will be asked if you want to edit this sector. Yes will drop you into the Edit Sector option -- from here follow the directions for option number 2. A "D" option will display the code you were looking for and a few bytes of following code in disassembled form. You will then be asked if you want to continue the search or print the screen contents.

If you want to search for an ASCII string, answer "A", then input EXACTLY what you are looking for. For example, if you want to know where, on a DOS disk, the phrase "Write DOS Files" is located, then enter "Write DOS Files".

6) DISK COPY

Select option number 6. This is basically a straight forward copy utility, prompting for source and destination disks. This copy utility is intelligent. It will read as many sectors as the buffer size allows. If a source sector is empty, then it is not stored. Since SHERLOCK takes approximately 26K to run, there is a 22K buffer in a 48K computer. If the disk being copied is less than 24K the copy will be accomplished with one pass. A maximum of 4 passes is required if the source disk is full. If while copying, an error is encountered from the source disk, you will be prompted to insert the destination disk. After the buffer has been written out, you will be told which sector was not read. You will be given four choices:
1) Retry Sector
2) Continue (with next sector)
3) Skip (to next) track
4) End copy

Should there be an error in writing to a disk, you will be asked if you would like to retry the write.

SHERLOCK also offers a two drive copy utility. The functions work the same as described above, but there will be no prompts to change disks, it will automatically read and write from drive 1 to drive 2. Sherlock has write WITHOUT verify as it's default. Should this not be acceptable, see option 11 for disk configuration. Also, regardless of the configuration, if you use the two drive copy option, the source drive will always be drive 1 and the destination drive will always be drive 2.

7) DISK DIRECTORY

Select option number 7. This gives a Disk Directory for DOS disks. Information given includes the file name, status of the file, starting sector, length of file, and the file number. If you want a print out of the directory, just press "P".

8) FMS SECTOR TRACE

Select option number 8. This is a utility to trace sector links for DOS files. Enter the file number determined by option number 7, and the sector link trace will be displayed. Press "P" and the screen display will be printed.

9) NUMBER CONVERSION

Select option number 9. To convert a decimal number to a hexadecimal number, just type in the decimal number and the conversion will automatically be printed. If you want a hexadecimal to decimal conversion, just preceed the hexadecimal number with a '$' and the decimal number will be printed.

10) FORMAT DISK

Select option number 10. This option is really meant as a compliment to the Disk Copy utility. This option will format a diskette, but will not write the DOS boot sectors or set up the VTOC and Disk Directory. If you need a formatted diskette for the copy routine, then this format is fine, because every sector is copied. If you need a formatted diskette for use with DOS files, do not use this format. Boot a DOS disk and format with option I.

11) CONFIGURE DRIVE

Select option number 11. By using this option you can have SHERLOCK communicate with up to 4 ATARI 810 Disk Drives or 8 PERCOM RFD Disk Drives. At this point you may also decide if you would like to write to the disk drive with or without verify.

ATARI is a registered trademark of WARNER COMMUNICATIONS

NOTES

NOTES

NOTES

NOTES

NOTES

RANTOM

Microcomputer Software

BOX 5480 AVON. CO 81620